

## Emergency power supply 24 V / 150 A



**Part-No. 581721**

Part of EN 54-16 approval

Emergency manager for use as emergency power supply of an Voice Alarm ? application.

### Features:

- Emergency power supply in 1 HU housing
- 3 individually fused outputs for control devices (DOM)
- 6 individually fused high power outputs for power amplifiers
- Approval according to EN 54-4 (A2)
- LED indicators for power, battery, consumer
- Potential free contacts for forwarding of error messages
- Battery capacity up to 225 Ah
- Maximum output 150 A

Rated voltage	230 V AC
Rated frequency	50 ... 60 Hz
Output voltage	24 V DC
Output current	max. 150 A
Ambient temperature	-5 °C ... 45 °C (at 100 % load)
Storage temperature	-25 °C ... 85 °C
Air humidity	0 ... 95 %
Weight	approx. 6 kg
Dimensions	W: 483 mm H: 88 mm D: 395 mm (2 HU, 19")



2 batteries of the same kind are required for each emergency power supply.



Delivery time on request.

### Accessories:

- 581730 Battery for emergency power supply 12 V / 105 Ah
- 581731 Battery for emergency power supply 12 V / 150 Ah