

essernet redundant switch for IQ8Control



Part-No. 784844.10

The essernet changeover switch allows the uninterruptable redundant changeover between trunk and spare line, if the essernet data line is disturbed. The switch is powered through the fire alarm control panel. Maximum distance between each switch 1,000 m.

Operating voltage	8 ... 14 V DC
Current consumption @ 12 V DC	approx. 60 mA
Ambient temperature	-10 °C ... 70 °C
Storage temperature	-20 °C ... 80 °C
Type of protection	IP 65
Housing	die-cast aluminium
Air humidity	< 95 %
Color	gray
Weight	approx. 730 g